

# IPS225

## Pro Series Track Current Limiter - 120V

### DESCRIPTION

Current limiters are intended to be installed at every track feed location in place of a standard non-limiting feed. These feeds incorporate circuit breaker for each circuits (2) which are designed to limit available wattage to the track.

### FEATURES

- Up to six different amperages
- Three different finishes
- (2) Self luminous ON/OFF breaker switches allow for different wattages on each circuit
- Plastic polycarbonate cover

### ELECTRICAL


- 120V/60Hz capacity
- All wiring should meet National and local electrical codes
- Use 12 gauge, 90°C minimum supply wire

### LISTING

UL Listed to US and Canadian standards for dry locations



JOB NAME		CATALOG NUMBER	
NOTES		TYPE	



Example: IPS225W-2A-2A

Current Limiter	Finish	Circuit 1 Breaker	Circuit 2 Breaker
IPS225	<input type="checkbox"/> <b>W</b> (White)	<input type="checkbox"/> <b>-1A</b> (120W / 1A)	<input type="checkbox"/> <b>-1A</b> (120W / 1A)
	<input type="checkbox"/> <b>B</b> (Black)	<input type="checkbox"/> <b>-2A</b> (300W / 2.5A)	<input type="checkbox"/> <b>-2A</b> (300W / 2.5A)
	<input type="checkbox"/> <b>SV</b> (Silver)	<input type="checkbox"/> <b>-5A</b> (600W / 5A)	<input type="checkbox"/> <b>-5A</b> (600W / 5A)
		<input type="checkbox"/> <b>-7A</b> (900W / 7.5A)	<input type="checkbox"/> <b>-7A</b> (900W / 7.5A)
		<input type="checkbox"/> <b>-10A</b> (1200W / 10A)	<input type="checkbox"/> <b>-10A</b> (1200W / 10A)
		<input type="checkbox"/> <b>-12A</b> (1440W / 12A)	<input type="checkbox"/> <b>-12A</b> (1440W / 12A)